



PM3300

600A AC CURRENT TRANSDUCER

PM3301

600A AC/DC CURRENT TRANSDUCER

- Operates on ACV /DCV range of a digital multimeter to get AC or DC current reading
- Wide frequency response for true RMS ACA measurement
- Zero adjustment for DCA measurement
- Safety as per IEC1010-1 Cat.III 600V

Technical specifications

PM3300:

ACA: 60A /600A, $\pm 2\%$ rdg+5dgt

PM3301:

ACA: 60A /600A, $\pm 2\%$ rdg+5dgt

DCA: 60A /600A, $\pm 2\%$ rdg+5dgt

Signal output ratio:

60A: 10mV/1A; 600A: 1mV/1A

Frequency response: 45Hz~1kHz

Max. clamp opening: $\Phi 35\text{mm}$

Max. wire length: 1m

Battery: 1.5Vx2, AAA size

Dimensions: 187x66x34mm, 180.5g approx.

PEAKMETER®

by Sinometer

www.peak-meter.cn

Email: sales@peak-meter.cn